




When the instrument is first powered up, it scrolls through the following pages.



To set up the preliminary configuration, press the SET button for at least 3 sec.

1

Choose the wiring mode




Press



The mode will flash

3.4.3=three-phase, 4 wires, 3 currents
3.3.2=three-phase, 3 wires, 2 currents
1ph=single-phase

Modify the mode using



Confirm with



Appuyer 2 fois sur



2

Enter the required FSA




Press



The value will flash

Available values:
500 A / 4 kA / 20 kA.

Modify the value using



Confirm with



The FSA corresponds to the current range

For $I \leq 500$ A, use the **500 A** range

For $500 \text{ A} \leq I \leq 4 \text{ kA}$, use the **4 kA** range

For $4 \text{ kA} \leq I \leq 20 \text{ kA}$, use the **20 kA** range

3

Save and exit

For 3 sec, press



Confirm with

